



Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: hslecsales@aliyun.com

Web: www.reactorinchina.com www.hslec.com



Selection Guide of Three Phase Line Reactor

1. Three-phase Line Reactor Compatible to the Inverter (FRNG/P Series)

Line Reactor Compatible to FUJI Inverter(FRNG/P)									
Rated AC Source Voltage V	Motor Rated Power kw	(FUJI) FUJI Inverter			(ACR) Three Phase Line Reactor				
		Model	Output Voltage V	Output Current A	Phase Current A	Phase Inductance	FUJI Ordering No.	HSL Ordering No.	
3AC 200 +10% -15%	0.4	FVR004G7S-2EX	3AC 50Hz 200 60Hz 200 220 230		3	0.917	ACR2-0.4A	HSL119-F01	
	0.75	FVR008G7S-2EX			5	0.193	ACR2-0.75A	HSL119-F02	
	1.5	FVR015G7S-2EX			8	0.295	ACR2-1.5A	HSL119-F03	
	2.2	FVR022G7S-2EX			11	0.213	ACR2-2.2A	HSL119-F04	
	3.7	FVR037G7S-2EX			17	0.1275	ACR2-3.7A	HSL119-F05	
	5.5	FVR055G7S-2EX			25	0.0877	ACR2-5.5A	HSL119-F06	
	7.5	FVR075G7S-2EX			33	0.065	ACR2-7.5A	HSL119-F07	
	11	FVR110G7S-2EX			48	0.0456	ACR2-11A	HSL119-F08	
	15	FVR150G7S-2EX			59	0.0349	ACR2-15A	HSL119-F09	
	18.5	FVR185G7S-2EX			74	0.0286	ACR2-18.5A	HSL119-F10	
	22	FVR220G7S-2EX			87	0.024	ACR2-22A	HSL119-F11	
	30	FRN30G9/P9S-2JX			115	200	0.0108	ACR2-37A	HSL119-F12
	37	FRN37G9/P9S-2JX			145				
	45	FRN45G9/P9S-2JX			180	270	0.0075	ACR2-55A	HSL119-F13
	55	FRN55G9/P9S-2JX			215				
	75	FRN75G9/P9S-2JX			283	390	0.00545	ACR2-75A	HSL119-F14
90	FRN90G9/P9S-2JX	346	460	0.00473	ACR2-90A	HSL119-F15			
110	FRN110G9/P9S-2JX	415	500	0.00425	ACR2-110A	HSL119-F16			