



Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: hslecsales@aliyun.com

Web: www.reactorinchina.com www.hslec.com

ZSSC Phase shifting rectifier transformer

Basic Order Data need customer to provide:

- 1.Rated HV And LV
- 2.Rated Capacity
3. Phase-shifting Angle
- 4.Cooling type :AN or AF
- 5.Protection grade



Technical Data for your reference

Rated Voltage: 10±5%/0.08-0.61KV

Rectifier phase-shifting Angle: ±7.5°、 ±10°、 ±12°、 ±15°、 ±22.5°、 ±25°

Model	Secondary voltage	Impedance	Loss		No-load current	Dimension	Track guage	Weight
	(V)		No-load	Loaded		LxBxH		
		(%)	(Watt)		(%)	without shell	L(mm)	(kg)
ZSSC-143/10	80	5.35	635	2390	0.56	1250X750X1150	820	1020
ZSSC-234/10	145	5.4	810	3210	0.48	1320X800X1260	820	1210
ZSSC-490/10	465	5.88	1485	4680	0.42	1640X1100X1420	820	2490
ZSSC-600/10	580	6.12	1570	5220	0.38	1700X1200X1560	1070	2850
ZSSC-1250/10	515	6.54	2280	8760	0.34	1900X1400X1720	1070	4240
ZSSC-2000/10	610	7.46	3920	11200	0.31	2200X1600X1980	1435	6820



Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: hslecsales@aliyun.com

Web: www.reactorinchina.com www.hslec.com

Note :1. We just listed the transformer we had manufactured for our customers in the above table. We can also provide you all kinds of transformers according to your requirements.

2. Data included in the table for reference only. If you need more information, please contact us .

Note :1、 When the rated high-voltage is 11, 10.5, 6.6, 6.3, 3.0KV, rated low voltage is non-standard product can refer the above outline dimension.

2、 Data included in the table for reference only. For more information please contact us .