



**Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.**

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: [hslecsales@aliyun.com](mailto:hslecsales@aliyun.com)

Web: [www.reactorinchina.com](http://www.reactorinchina.com) [www.hslec.com](http://www.hslec.com)

**S11-M-30~2500/6~10series no excitation**

**regulating distribution transformer**

Basic Order Data need customer to provide:

1. Rated HV and LV
2. Rated Capacity
3. Joint Group: Yyn0 or Dyn11
4. Using condition



Technical Data for your reference

Rated Capacity (KVA)	Vector Group	(KV) Voltage Combination		No-load Current	No-load Loss	Load Loss	Impedance
		(H.V.)	(L.V.)	%	W	(75°C)W	%
10	Yynoor OR Dyn11	6+5%OR 6.3+5% OR 10+5%	0.4	3.8	55	310	4.0
20				3.0	80	475	4.0
30				2.1	100	600	4.0
50				2.0	130	870	4.0
63				1.9	150	1040	4.0
80				1.8	180	1250	4.0
1400				1.6	200	1500	4.0
125				1.5	240	1800	4.0
160				1.4	290	2200	4.0
200				1.3	340	2600	4.0
250				1.2	400	3050	4.0



**Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.**

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: [hslecsales@aliyun.com](mailto:hslecsales@aliyun.com)

Web: [www.reactorinchina.com](http://www.reactorinchina.com) [www.hslec.com](http://www.hslec.com)

315				1.0	480	3650	4.0
400				1.0	570	4300	4.0
500				1.0	680	5150	4.0
630				0.9	810	6200	4.5
800				0.8	980	7500	4.5
1000				0.7	1150	10300	4.5
1250				0.6	1360	12000	4.5
1600				0.6	1640	14500	4.5
2000				0.6	1720	17800	5.5
2500				0.5	12020	20700	5.5

Note: Data included in the table are for reference only. For more information please contact us.