



Qin Huangdao Huashenglong Electrical Equipment Co.,Ltd.

Tel :0086-335-8560000

Fax:0086-335-8515333

Mobile(WhatsApp) :0086-13483376954

Skype:happyeveryday934

Email: hslecsales@aliyun.com

Web: www.reactorinchina.com www.hslec.com



Selection Guide of Three Phase Line Reactor

1. Line Reactor Compatible to the Allen-Bradley Inverter

A-B400								
Rated Voltage(V)	Reactance	Inverter			Three Phase Line Reactors			
		Motor Power (KW)	A-B Inver Model 50/60HZ	Rated Current (A)	Basic Current (A)	Max. Continues Current (A)	AB Ordering No. IP00(MENA1)	HSLEC Ordering No.
200~240	3%	5.5	22C-B024N103	24	25	37.5	1321-3R(A)25-A	HSL119-AB01
		7.5	22C-B033N103	33	35	52.5	1321-3R(A)35-A	HSL119-AB02
		11	22C-B049N103	49	45	67.5	1321-3R(A)45-A	HSL119-AB03
		15	22C-B065N103	65	55	82.5	1321-3R(A)55-A	HSL119-AB04
		18.5	22C-B075N103	75	80	120	1321-3R(A)80-A	HSL119-AB05
		22	22C-B090N103	90				
		30	22C-B120N103	120	100	150	1321-3R(A)100-A	HSL119-AB06
	37	22C-B145N103	145	130	195	1321-3R(A)130-A	HSL119-AB07	
	5%	5.5	22C-B024N103	24	25	37.5	1321-3R(A)25-B	HSL119-AB08
		7.5	22C-B033N103	33	35	52.5	1321-3R(A)35-B	HSL119-AB09
		11	22C-B049N103	49	45	67.5	1321-3R(A)45-B	HSL119-AB10
		15	22C-B065N103	65	55	82.5	1321-3R(A)55-B	HSL119-AB11
		18.5	22C-B075N103	75	80	120	1321-3R(A)80-B	HSL119-AB12
		22	22C-B090N103	90				
30		22C-B120N103	120	100	150	1321-3R(A)100-B	HSL119-AB13	
37	22C-B145N103	145	130	195	1321-3R(A)130-B	HSL119-AB14		